



## ■ Features :

- Universal AC input / Full range
- Built-in active PFC function, PF>0.93
- Protections: Short circuit / Overload / Over voltage / Over temperature
- Built-in constant current limiting circuit
- \* Remote ON-OFF control(Optional)
- LED indicator for power on
- 100% full load burn-in test
- Fixed switching frequency at PFC:67KHz PWM:134KHz
- 3 years warranty



## **SPECIFICATION**

P	<b>c</b> SUS US UL60950-1
---	---------------------------

MODEL		SP-150-3.3	SP-150-5	SP-150-7.5	SP-150-12	SP-150-13.5	SD-150-15	SP-150-24	SP-150-27	SP-150-48			
WODEL													
ОИТРИТ	DC VOLTAGE	3.3V	5V	7.5V	12V	13.5V	15V	24V	27V	48V			
	RATED CURRENT	30A	30A	20A	12.5A	11.2A	10A	6.3A	5.6A	3.2A			
	CURRENT RANGE	0 ~ 30A	0 ~ 30A	0 ~ 20A	0 ~ 12.5A	0 ~ 11.2A	0 ~ 10A	0 ~ 6.3A	0 ~ 5.6A	0 ~ 3.2A			
	RATED POWER	99W	150W	150W	150W	151.2W	150W	150W	151.2W	153.6W			
	RIPPLE & NOISE (max.) Note.2		100mVp-p	100mVp-p	100mVp-p	100mVp-p	100mVp-p	150mVp-p	150mVp-p	250mVp-p			
	VOLTAGE ADJ. RANGE	3.14 ~ 3.63V	4.75 ~ 5.5V	7.13 ~ 8.25V	11.4 ~ 13.2V	12.8 ~ 14.9V	14.3 ~ 16.5V	22.8 ~ 26.4V	25.7 ~ 29.7V	45.6 ~ 52.8V			
	VOLTAGE TOLERANCE Note.3	±2.0%	±2.0%	±2.0%	±2.0%	±2.0%	±2.0%	±1.0%	±1.0%	±1.0%			
	LINE REGULATION	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%			
	LOAD REGULATION	±1.0%	±1.0%	±1.0%	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%			
	SETUP, RISE TIME	700ms, 40ms at full load											
	HOLD UP TIME (Typ.)	20ms at full load											
	VOLTAGE RANGE Note.5	85 ~ 264VAC 120 ~ 370VDC											
	FREQUENCY RANGE	47 ~ 63Hz											
	POWER FACTOR (Typ.)	PF>0.93/230VAC PF>0.97/115VAC at full load											
INPUT	EFFICIENCY (Typ.)	73%	77.5%	81%	84%	84%	85%	85%	85%	85%			
	AC CURRENT (Typ.)	2.5A/115VAC	2.5A/115VAC 1.2A/230VAC										
	INRUSH CURRENT (Typ.)	COLD START 45A/230VAC											
	LEAKAGE CURRENT	<2mA/240VAC											
	105 ~ 150% rated output power												
	OVERLOAD Protection type: Constant current limiting, recovers automatically after fault condition is removed												
PROTECTION	3.63 ~ 4.46V   5.5 ~ 6.75V   8.25 ~ 10.13V   13.2 ~ 16.2V   14.85 ~ 18.2V   16.5 ~ 20.25V   26.4 ~ 32.4V   29.7 ~ 36.45V   52.8 ~ 64.00									52.8 ~ 64.8V			
	OVER VOLTAGE	Protection type: Shut down o/p voltage, re-power on to recover											
	OVER TEMPERATURE	YER TEMPERATURE Shut down o/p voltage, recovers automatically after temperature goes down											
FUNCTION	REMOTE CONTROL(OPTION)	CN1:4 ~ 10VDC POWER ON, <0 ~ 0.8VDC POWER OFF											
	WORKING TEMP.	-10 ~ +55°C (Refer to output load derating curve)											
	WORKING HUMIDITY	20 ~ 90% RH non-condensing											
ENVIRONMENT	STORAGE TEMP., HUMIDITY	-20 ~ +85°C, 10 ~ 95% RH											
	TEMP. COEFFICIENT	±0.05%/°C (0~50°C)											
	VIBRATION	10 ~ 500Hz, 2G 10min./1cycle, 60min. each along X, Y, Z axes											
	SAFETY STANDARDS	UL60950-1 approved											
SAFETY &	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC											
EMC	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C / 70% RH											
(Note 4)	EMC EMISSION	Compliance to EN55032 (CISPR32) Class B,EN61000-3-2,-3											
	EMC IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11; ENV50204, EN55024, light industry level, criteria A											
OTHERS	MTBF	191.2K hrs min. MIL-HDBK-217F (25°C)											
	DIMENSION	199*99*50mm (L*W*H)											
	PACKING	0.76Kg; 20pcs	s/16.4Kg/1.210	CUFT									
NOTE	1. All parameters NOT specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature.  2. Ripple & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor.  3. Tolerance: includes set up tolerance, line regulation and load regulation.  4. The power supply is considered a component which will be installed into a final equipment. All the EMC tests are been executed by mounting the unit on a 360mm metal plate with 1mm of thickness. The final equipment must be re-confirmed that it still meets EMC directives. For guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies." (as available on http://www.meanwell.com)  5. Derating may be needed under low input voltages. Please check the derating curve for more details.												
	※ Product Liability Disclaimer	sclaimer: For detailed information, please refer to https://www.meanwell.com/serviceDisclaimer.aspx											



